



THERMNIGHT

Quick Start

Quick Start

Congratulations on your DNT Optics purchase. Here is a simple guide that lists each of the button functions to help you understand their use along with steps to help with the initial setup of your optic.

Power Button

Short press Enters / Exits Standby
Long press Powers On / Off

Color Mode Switch Button

Color Mode Switch Button has many features built into it:

main screen: Thermal

Short press Changes Color Palettes
Long press Manual NUC^①

main screen: Digital Day / Night

Short press Adjusts IR Brightness (in Night Mode)
Long press Switches Between Day & Night Mode



Menu Button


Main Screen: Short press Switches Reticle Color
Long press Enters Menu

PIP Button

Main Screen: Short press Sets Screen Brightness
Long press Turns On / Off PIP^②

Record Button

Main Screen: Short press Starts RAV^③ Recording (Manual Mode)
Long press Starts / Ends Recording



In the Settings Menu, the four buttons work like your TV remote control. Use **Menu** or **Record** button to move your cursor. Use the **PIP** button to select and **Color Mode Switch** button to cancel and go back.

^① NUC: Non-Uniformity Calibration
^② PIP: Picture-in-Picture
^③ RAV: Recoil Activate Video

How to connect to DNT App

STEP ①



Ensure the battery cap is tightly screwed on. This compresses the battery and prevents your optic from shutting off under recoil.

STEP ②



A long press of the **Power Button** will turn the optic on.

STEP ③



Long press the **Menu Button** to open the Settings Menu.

STEP ④



Find the "Connection" icon, then short press the **PIP Button** twice to enter and confirm the Wi-Fi setting is enabled. Confirm Wi-Fi is on by looking at the icon. Wi-Fi on (📶), Wi-Fi off (🚫).

STEP ⑤

Download DNT App.




Android



iOS

STEP ⑥

Open DNT App, select "Add Device", and select ThermNight Multispectral. This will open Wi-Fi Networks.



STEP ⑦

Device will display as [Device Naming Protocol]. Select TNC[Model]_[SerialNumber]. Device Wi-Fi Password is 12345678.

- Android Users select "Always Connect"
- Apple Users ensure "Auto-Join" is enabled
- Connection will show "Connected Without Internet". This is correct. Please return to the DNT App.

STEP ⑧

Your optic will now show "connected" in blue underneath your paired device.

